

## Model REC-558U ROBO\*CRIMP™ 6 Ton Battery Powered Compression Tool - 1.8" Jaw Opening

The Huskie REC-558U was designed to squeeze commonly used service entrance connectors, including lugs, sleeves, H-Taps and C-Taps. The rapid advance feature allows the operator quicker compression cycles. In addition to the rapid advance feature, it also has incorporated an electronic counter that will allow a service technician to read the number of compression cycles the tool has made. Also, the new tool housing has been reinforced to improve durability during heavy field use.

A factory pre-set bypass cartridge assures a six ton compression every time. The REC-558U accepts either "W" or "O" type dies. The D3 nest die comes standard with the tool. Always consult your connector manufacturer for proper die/connector combinations.

Like the REC-458, the REC-558U will accept the optional 25CAT cutter head attachment. Quick release pins allow the operator to change between compression and cutter head in one minute with no springs or pins to lose.

\*Will not cut ALL 500 MCM copper cable consult factory.

- Interchangeable Cutter Head
- Operates in Confined Underground Spaces
- Tested up to 75KV
- Accepts "W" & "O" Type Dies
- 5th Generation of the Original ROBO\* CRIMP
- Rapid Advance
- External Pressure Adjustment
- One Hand Operation
- 6 Ton Output



### CAT25 (Optional) Specifications:

Capacity	500 MCM Cu*
Jaw Opening	1"
Description	Optional Cutter attachment for the REC-558U

### Standard ROBO\* Kit includes:

- 1 Battery Powered Tool
- 1 Carrying Strap
- 1 Carrying Case
- 2 BP-70E Batteries
- 1 CH-35R 25 minute AC Charger

### Specifications:

Output	6 ton
Weight	8 lbs. with battery
Size	13"L x 12"H x 2.5"W
Jaw Opening	1.8"

### Crimping Estimates:

	<u>BP-70E</u>
#6 Cu/Al	210
1/0 Cu/Al	160
4/0 Cu/Al	125

### Connector Range:

Lugs and Splices	#8-500 MCM Cu #8-300 MCM Al
H-Taps	Up to 4/0 - 4/0

### Order Data:

Model #	Description
REC-558U	Battery Powered Compression Tool Standard Kit

To custom order a different tool kit battery and charger combination:

### Add the following suffixes to the tool model number:

SM	2 BP-70EI "Smart" LED Indicator Batteries
DC	1 CH-70DCH Charger 12 Volt DC Charger
MH	2 BP-70MH High Capacity Nickel Metal Hydride Battery with 30% more power output

### Optional Accessories:

BP-70E	Replacement Battery
BP-70EI	LED Indicator "Smart" Battery
BP-70MH	High Capacity Battery - Nickel Metal Hydride
CH-35R	25 Minute Charger
CH-70DCH	12V DC Battery Charger

NOTE: Pricing will vary according to tool kit combination.

Huskie Tools, Inc  
198 N. Brandon Dr.  
Glendale Heights, IL 60139-2025

Fax: 630-790-2626  
E-mail: info@huskietools.com

© 2006 Huskie Tools, Inc.

800.860.6170



When it's on the line, you count on Huskie Tools.